



CPU Instance Provider

provider overview

description

The CPU Instance Provider is a Web Based Enterprise Management (WBEM) Instance Provider that fetches CPU-related information from HP PA-RISC Servers, running HPUX. This provider is compliant with the Common Information Model (CIM) 2.7.2 Schema, proposed by the Distributed Management Task Force (DMTF). The provider requires HP WBEM Services for HP-UX Version 2.0 installed on the system.

The CPU Instance Provider allows any client program, compliant with the CIM 2.7.2 Schema, to query for information about the managed system's processors.

The CPU Instance Provider implements the Processor-related CIM classes, proposed in the DMTF CIM 2.7.2 revision. In addition to the properties that belong to the standard CIM classes, the CPU Instance Provider serves information that is specific to HP Servers, by implementing HP-specific CIM classes, derived from the standard DMTF classes.

The following MOF classes are handled by the CPU Instance Provider:

- HP_Processor and HPUX_Processor
HP_Processor (subclass of CIM_Processor) and HPUX_Processor (subclass of HP_Processor) represent "logical" information about the processors, including status, the family of the processors, clock-speeds, etc.
- HP_ProcessorChip
HP_ProcessorChip (subclass of CIM_Chip) represents "physical" information about the processor, such as the Processor Firmware Revision, Architecture Revision, etc.
- HP_ProcessorLocation and HPUX_ProcessorLocation
HP_ProcessorLocation (subclass of CIM_Location) and HPUX_ProcessorLocation (subclass of HP_ProcessorLocation) captures information about the physical location of the processor-chip and the core of the processor, as seen from the physical perspective. This includes identification of which Cell the processor-chip resides in, the Slot numbers, Cabinet numbers, etc.

In addition, the CPU Instance Provider also implements association classes to associate the instances of the different CIM classes mentioned above. These include:

- HP_RealizesProcessor (subclass of CIM_Realizes): This class identifies which logical Processor (HP_Processor) instance is associated to which Physical Processor (HP_ProcessorChip) instance.
- HP_ProcessorChipInLocation (subclass of CIM_PhysicalElementLocation): This class indicates the physical location (HP_ProcessorLocation) corresponding to a specific processor chip (HP_ProcessorChip).

The MOF classes mentioned above (i.e. all MOF classes prefixed with "HP_") are HP-specific extensions to the CIM Schema, and are registered in the "root/cimv2" namespace.

For all the MOF classes mentioned above, the CPU Instance Provider supports the following standard CIM Operations:

- enumerateInstanceNames()
- enumerateInstances()
- getInstance()

The following CIM operations are not supported by the CPU Instance Provider:

- createInstance()

- o deleteInstance()
- o modifyInstance()

The CPU Instance Provider is not a CIM Method Provider, and does not support extrinsic method invocation on instances on any of the MOF classes mentioned above. The invocation of any of these methods will result in a CIM_ERR_NOT_SUPPORTED exception.

requirements

HP WBEM Services 2.0

release history

This provider will be made available via web release in Mar 2004.

supported managed resources

This provider provides "logical" information about system CPU's, "physical" attributes of the Processor-Chip, and details of the physical-location of the processor.

Please note that the CPU Instance Provider provides only the information about the above resources. It does not provide any management, diagnostic or configuration capabilities for the above resources.

setting up this provider

installing this provider

The installation of the appropriate bundle (SysFaultMgmt32PA or SysFaultMgmt64PA) will set up this provider.

- Choose SysFaultMgmt32PA for 32bit PA-RISC platforms.
- Choose SysFaultMgmt64PA for 64bit PA-RISC platforms.
- Choose SysFaultMgmt32PA for 32/64 bit platforms booted in 32 bit mode.
- Choose SysFaultMgmt64PA for 32/64 bit platforms booted in 64 bit mode.

On installation, the shared-library files, executable binaries, configuration files and MOF definition and registration files will be available in the /opt/sfm/ directory, as follows:

- The provider library is libcpuprovider.1. This is available in /opt/sfm/lib/, along with all the other libraries it uses to implement the CPU Instance provider. A symbolic link is made in /opt/wbem/providers/lib/libcpuprovider.sl to link to the libcpuprovider.1 library in /opt/sfm/lib/.
- The CIM MOF files, containing the definitions of the HP-specific MOF classes, (namely HPProcessor.mof) will be available in /opt/sfm/schemas/mof. This directory will also include the provider registration file, namely CpuInstanceProviderR.mof. Note: All the HP-specific MOF classes will be registered under the "root/cimv2" namespace.
- The /opt/sfm/bin/ directory will contain the binary executable files that are used by the CPU Instance Provider. This includes the "fmControl" utility, that is used for sending notifications to the CPU Instance Provider (e.g. on updation to the configuration file).
- The /opt/sfm/conf/ directory will contain the (XML) configuration files of the CPU Instance Provider, and all the modules that this provider uses.
- The /opt/sfm/msgcat/ directory will contain the catalog files for all the supported locales. (This is used for the localization of the message strings in CPU Instance Provider).
- The /opt/sfm/log/ directory will contain log files generated during the execution of the CPU Instance Provider.

The CPU Instance Provider will be supported on the following platforms:

- o PA-RISC servers (HP-UX 11i v1) - 32-Bit Platforms
 - A180, A180C

- D200, D210, D280 (HVERS 0x589 not 0x5A9), D350, D360
- K100, K210, K220, K360 (HVERS 0x591 not 0x5A6), K370, K380, K400, K410, K420
- PA-RISC servers (HP-UX 11i v1) – 32/64 Bit Platforms
 - D390
 - K450, K460, K570, K580
- PA-RISC servers (HP-UX 11i v1) - 64-Bit Platforms
 - A400, A500
 - K250, K260, K360 (HVERS 0x5B6 not 0x5A6), K370, K380
 - L1000, L2000, L3000
 - N4000
 - rp7410
 - rp8400
 - SD16000, SD32000, SD64000

Configuring this provider

CPU Provider uses a common configuration file along with Memory Instance Provider and EMSWrapper Indication Provider. So editing the configuration file will affect the other two providers as well. The configuration file can be found in – /opt/sfm/conf/FMLoggerConfig.xml

The file specifies the logging threshold severity, and the location of the log-file. The contents of the file are as follows:

```
<SFMConfig>
  <LoggerConfig>
    <Severity> WARNING </Severity>
    <Target> /opt/sfm/log/sfm.log </Target>
  </LoggerConfig>
</SFMConfig>
```

In order to change the logging configuration, the following steps are to be followed:

1. Edit the configuration file /opt/sfm/conf/FMLoggerConfig.xml to change the threshold logging level and/or target.

a) Threshold: Possible values are (in increasing severity)

```
INFORMATIONAL
WARNING
ERROR
CRITICAL
```

NOTE The INFORMATIONAL logging severity will generate a lot of log-messages. It is strongly advised not to use this severity level for a long time, for the generated log-files may use a lot of disk space. The default (and recommended) threshold in the runtime environment is WARNING.

b) Target: Possible values include:

- (i) STDOUT: All log messages are delivered to console.
- (ii) The complete path to the file where the log messages are to be written

NOTE: The current implementation of the logging mechanism assumes that the path to the log file (target specified in the configuration file) already exists. i.e., if the target is specified as "/abc/def/ghi.log", the path "/abc/def/" should already exist, and should be writeable by root-user.

2. Run /opt/sfm/bin/fmControl program, to specify the changed configuration file. i.e.

```
$ /opt/sfm/bin/fmControl /opt/sfm/conf/FMLoggerConfig.xml
```

Note that the complete path of the configuration file must be provided to the fmControl program.

using this provider

schema supported by this provider

The "Description" section explains in brief the different MOF classes supported by the CPU Instance Provider. The following tables list all the supported properties corresponding to these MOF classes, along with the properties inherited from the standard CIM MOF classes, as per CIM 2.7.2 schema specifications.

Note: All key properties corresponding to the CIM classes are supported by the CPU Instance Provider. The few non-key properties not supported (currently) by the CPU Instance Provider are not listed below.

Note:

1. All key properties corresponding to the CIM classes are supported by the CPU Instance Provider.
2. The non-key properties that are not supported by the CPU Instance Provider are not listed below.

Table 1: HP_Processor and HPUX_Processor Properties (Logical Processor Information):

Table 1 describes the properties of the HP_Processor and HPUX_Processor CIM classes. It has three columns. The first is the property name (including type and units), the second is the property inheritance (indicating which class or superclass defines the property), and the third is the property's value and data source. Each row describes a property.

Property name	property inheritance	property value (and data source)
string Caption	Inherited from CIM_ManagedElement	This value is always returned as "Processor".
string Description	Inherited from CIM_ManagedElement	For PA-RISC servers, this string is set to "This is a PA RISC Processor, with the following details: ", followed by location-details for the processor. Location details include (where available): <ol style="list-style-type: none"> 1. Cabinet Number 2. Card Cage Number 3. Backplane Number 4. Cell Slot number 5. Slot number 6. SPU Number (as seen by the OS instance) 7. Hard Physical Address (for PA-RISC Servers)
string ElementName	Inherited from CIM_ManagedElement	For PA-RISC Servers, this string is set to "PA RISC Processor".
String Name	Inherited from CIM_ManagedSystemElement	For PA-RISC Servers, this string is set to "PA RISC Processor".
uint16 OperationalStatus []	Inherited from CIM_ManagedSystemElement	The Value-Map associated with this property (as per the CIM 2.7.2 Schema Specification) is as follows: <pre>ValueMap {"0", "1", "2", "3", "4", "5", "6", "7", "8", "9", "10", "11", "12", "13", "14", "15", "16", "17"},</pre> Values {"Unknown", "Other", "OK", "Degraded", "Stressed", "Predictive Failure", "Error", "Non-Recoverable Error", "Starting", "Stopping", "Stopped", "In Service", "No Contact", "Lost Communication", "Aborted", "Dormant", "Supporting Entity in Error", "Completed"} The OperationalStatus array contains multiple values, to indicate the different aspects of the CPU's status. The values returned in different scenarios are as follows: <ol style="list-style-type: none"> 1. If the processor is Configured and Active, the first element is 2 (for "OK"). 2. If the processor is Configured and Inactive, then the first element is 2 (for "OK") and the second element is 15(for "Dormant") 3. If the processor is Marked for configuration,

then the first element is set to 2 (for "OK") and the second element is set to 8 (for "Starting")

4. If the processor is Marked for Deconfiguration and Active, then the first element is set to 2 (for "OK") and the second element is set to 9 (for "Stopping").
5. If the processor is Marked for Deconfiguration and Inactive, then the first element is set to 2 (for "OK"), the second element is set to 15 (for "Dormant") and the third element is set to 9 (for "Stopping").
6. If the processor has errors, then the first element of this array is set to 6 (for "Error").

Note: Error information will be provided by consuming indications (of LPMC's) from the EMS Wrapper Provider.

7. If either the Deconfiguration status, or the Active status of the processor is unknown, or not retrievable, this array will contain a single element 0, indicating an "Unknown" status

string StatusDescriptions[]

Inherited from
CIM_ManagedSystemElement

This contains string descriptions for the status values returned in the Operational Status array described above. Each value in the StatusDescriptions array corresponds to the (localized) verbose status description for the value at the same index in the OperationalStatus array.

The Strings describing the different values in the OperationalStatus Array are as follows:

1. The Description string corresponding to a value of "2" in the OperationalStatus array is: "Processor is OK".
2. The Description string corresponding to a value of "15" in the OperationalStatus array is: "Processor is idle. There are no processes scheduled on this processor."
3. The Description string corresponding to a value of "8" in the OperationalStatus array is: "Processor is currently deconfigured, and will be configured in the next reboot."
4. The Description string corresponding to a value of "9" in the OperationalStatus array is: "Processor is currently configured, and will be deconfigured in the next reboot."
5. The Description string corresponding to a value of "6" in the OperationalStatus array is: "Processor is in Error".
6. The Description string corresponding to a value of "0" in the OperationalStatus array is: "Processor is in an UNKNOWN state".

For example, consider that the processor is Marked for Deconfiguration, and Active. The OperationalStatus array will be set such that:

1. OperationalStatus[0] = 2
2. OperationalStatus[1] = 9

Then, the StatusDescriptions array will correspondingly be set such that:

1. StatusDescriptions[0] = "Processor is OK"

		2. StatusDescriptions[1] = "Processor is currently configured, and will be deconfigured in the next reboot."
string SystemCreationClassName [Key]	Inherited from CIM_LogicalDevice	Fixed string "PG_ComputerSystem"
string SystemName [Key]	Inherited from CIM_LogicalDevice	The host name of the server.
string CreationClassName [Key]	Inherited from CIM_LogicalDevice	This is set to the name of the instantiated sub-class, i.e. "HPUX_Processor".
string DeviceID [Key]	Inherited from CIM_LogicalDevice	For PA-RISC Servers, this is set to the Hard Physical Address of the processor.
Uint16 Family	Inherited from CIM_Processor	<p>The Value-Map for this property looks as follows:</p> <pre>ValueMap {"1", "2", "3", "4", "5", "6", "7", "8", "9", "10", "11", "12", "13", "14", "15", "16", "17", "18", "19", "24", "25", "26", "27", "28", "29", "30", "31", "32", "33", "34", "35", "36", "37", "38", "39", "48", "49", "50", "51", "52", "53", "54", "55", "64", "65", "66", "67", "68", "69", "80", "81", "82", "83", "84", "85", "86", "87", "88", "96", "97", "98", "99", "100", "101", "112", "120", "121", "128", "130", "144", "145", "146", "147", "148", "149", "150", "160", "176", "177", "178", "179", "180", "181", "182", "183", "184", "190", "200", "201", "202", "250", "251", "260", "261", "280", "281", "300", "301", "302", "320", "350", "500"}</pre> <pre>Values {"Other", "Unknown", "8086", "80286", "80386", "80486", "8087", "80287", "80387", "80487", // 11 "Pentium(R) brand", "Pentium(R) Pro", "Pentium(R) II", "Pentium(R) processor with MMX(TM) technology", "Celeron(TM)", "Pentium(R) II Xeon(TM)", "Pentium(R) III", "M1 Family", "M2 Family", //24 "K5 Family", "K6 Family", "K6-2", "K6-3", "AMD Athlon(TM) Processor Family", "AMD(R) Duron(TM) Processor", "AMD29000 Family", //31 "K6-2+", "Power PC Family", "Power PC 601", "Power PC 603", "Power PC 603+", "Power PC 604", "Power PC 620", "Power PC X704", "Power PC 750", // 48 "Alpha Family", "Alpha 21064", "Alpha 21066", "Alpha 21164", "Alpha 21164PC", "Alpha 21164a", "Alpha 21264", "Alpha 21364", // 64 "MIPS Family", "MIPS R4000", "MIPS R4200", "MIPS R4400", "MIPS R4600", "MIPS R10000", // 80 "SPARC Family", "SuperSPARC", "microSPARC II", "microSPARC IIep", "UltraSPARC", "UltraSPARC II", "UltraSPARC Ili", "UltraSPARC III", "UltraSPARC IIIi", // 96 "68040", "68xxx Family", "68000", "68010",</pre>

		<pre> "68020", "68030", // 112 "Hobbit Family", "Crusoe(TM) TM5000 Family", "Crusoe(TM) TM3000 Family", "Weitek", "Itanium(TM) Processor", // 144 "PA-RISC Family", "PA-RISC 8500", "PA-RISC 8000", "PA-RISC 7300LC", "PA-RISC 7200", "PA-RISC 7100LC", "PA-RISC 7100", // 160 "V30 Family", "Pentium(R) III Xeon(TM)", "Pentium(R) III Processor with Intel(R) SpeedStep(TM) ""Technology", "Pentium(R) 4", "Intel(R) Xeon(TM)", // 180 "AS400 Family", "Intel(R) Xeon(TM) processor MP", "AMD AthlonXP(TM) Family", "AMD AthlonMP(TM) Family", "Intel(R) Itanium(R) 2", // 190 "K7", // 200 "IBM390 Family", "G4", "G5", // 250 "i860", "i960", "SH-3", "SH-4", "ARM", "StrongARM", // 300 "6x86", "MediaGX", "MII", "WinChip", "DSP", "Video Processor"}), For PA-RISC Servers, this property is set to "144", to indicate "PA RISC Processor Family". </pre>
Uint32 CurrentClockSpeed	Inherited from CIM_Processor	The clock speed of the processor, in MHz.
Uint16 DataWidth	Inherited from CIM_Processor	Width of the data-bus of the processor.
Uint16 LoadPercentage	Inherited from CIM_Processor	Loading of the processor, averaged over one minute, in percentage.
Uint16 Spuld	Inherited from HPUX_Processor	This is an ID of the processor as seen by the OS.

Table 2: HP_ProcessorChip properties

Table 2 describes the properties of the HP_ProcessorChip class. It has three columns. The first is the property name (including type and units), the second is the property inheritance (indicating which class or superclass defines the property), and the third is the property's value and data source. Each row describes a property.

property name	property inheritance	property value (and data source)
string Caption	Inherited from CIM_ManagedElement.	This value is always returned as "Processor".
string Description	Inherited from CIM_ManagedElement.	For PA-RISC Servers, this string is set to "This is a PA RISC Processor, with the following details: ", followed by location-details for the processor. Location details include (where available):

		<ol style="list-style-type: none"> 1. Cabinet Number 2. Card Cage Number 3. Backplane Number 4. Cell Slot number 5. Slot number 6. SPU Number (as seen by the OS instance) 7. Hard Physical Address (for PA-RISC Servers)
string ElementName	Inherited from CIM_ManagedElement	For PA-RISC Servers, this string is set to "PA RISC Processor".
String Name	Inherited from CIM_ManagedSystemElement	For PA-RISC Servers, this string is set to "PA RISC Processor".
Uint16 OperationalStatus	Inherited from CIM_ManagedSystemElement.	<p>The Value-Map associated with this property (as per CIM 2.7.2 Schema specifications) is as follows:</p> <pre>ValueMap {"0", "1", "2", "3", "4", "5", "6", "7", "8", "9", "10", "11", "12", "13", "14", "15", "16", "17"},</pre> <p>Values {"Unknown", "Other", "OK", "Degraded", "Stressed", "Predictive Failure", "Error", "Non-Recoverable Error", "Starting", "Stopping", "Stopped", "In Service", "No Contact", "Lost Communication", "Aborted", "Dormant", "Supporting Entity in Error", "Completed"}</p> <ol style="list-style-type: none"> 1. If the processor is Configured and Active, the first element is 2 (for "OK"). 2. If the processor is Configured and Inactive, then the first element is 2 (for "OK") and the second element is 15(for "Dormant") 3. If the processor is Marked for configuration, then the first element is set to 2 (for "OK") and the second element is set to 8 (for "Starting") 4. If the processor is Marked for Deconfiguration and Active, then the first element is set to 2 (for "OK") and the second element is set to 9 (for "Stopping"). 5. If the processor is Marked for Deconfiguration and Inactive, then the first element is set to 2(for "OK"), the second element is set to 15 (for "Dormant") and the third element is set to 9 (for "Stopping"). 6. If the processor has errors, then the first element of this array is set to 6 (for "Error"). <p>Note: Error information will be provided by consuming indications (of LPMC's) from the EMS Wrapper Provider.</p> <ol style="list-style-type: none"> 7. If either the Deconfiguration status, or the Active status of the processor is unknown, or not retrievable, this array will contain a single element 0, indicating an "Unknown" status
string StatusDescriptions[]	Inherited from CIM_ManagedSystemElement	This contains string descriptions for the status values returned in the Operational Status array described above. Each value in the StatusDescriptions array corresponds to the (localized) verbose status description for the value at the same index in the OperationalStatus

array.

The Strings describing the different values in the OperationalStatus Array are as follows:

1. The Description string corresponding to a value of "2" in the OperationalStatus array is: "Processor is OK".
2. The Description string corresponding to a value of "15" in the OperationalStatus array is: "Processor is idle. There are no processes scheduled on this processor."
3. The Description string corresponding to a value of "8" in the OperationalStatus array is: "Processor is currently deconfigured, and will be configured in the next reboot."
4. The Description string corresponding to a value of "9" in the OperationalStatus array is: "Processor is currently configured, and will be deconfigured in the next reboot."
5. The Description string corresponding to a value of "6" in the OperationalStatus array is: "Processor is in Error".
6. The Description string corresponding to a value of "0" in the OperationalStatus array is: "Processor is in an UNKNOWN state".

For example, consider that the processor is Marked for Deconfiguration, and Active. The OperationalStatus array will be set such that:

1. OperationalStatus[0] = 2
2. OperationalStatus[1] = 9

Then, the StatusDescriptions array will correspondingly be set such that:

1. StatusDescriptions[0] = "Processor is OK"
2. StatusDescriptions[1] = "Processor is currently configured, and will be deconfigured in the next reboot."

String Tag [Key]	Inherited from CIM_PhysicalElement	For PA-RISC Servers, this contains the Hard Physical Address of the processor.
String CreationClassName [Key]	Inherited from CIM_PhysicalElement	The name of the subclass being instantiated, i.e. "HP_ProcessorChip".
Uint16 ArchitectureRevision	Inherited from HP_ProcessorChip	The Value-Map of this property is as follows: ValueMap {"0", "1", "2", "3", "4", "5"}, Values {"Unknown", "Other", "PARISC 1.0", "PARISC 1.1", "PARISC 2.0", "Itanium Architecture"} The Value of this property indicates the Architecture of the processor: 0 for Unknown 1 for Other 2 for PA RISC 1.0 3 for PA RISC 1.1 4 for PA RISC 2.0
String FirmwareRevision	Inherited from HP_ProcessorChip	Firmware Recipe Number, identifying the Processor's Firmware Revision.

table 3: HP_ProcessorLocation and HPUX_ProcessorLocation properties

Table 3 describes the properties of the HP_ProcessorLocation and HPUX_ProcessorLocation classes. It has three columns. The first is the property name (including type and units), the second is the property inheritance (indicating which class or superclass defines the property), and the third is the property's value and data source. Each row describes a property.

property name	property inheritance	property value (and data source)
string Caption	Inherited from CIM_ManagedElement.	This value is always returned as "Processor".
string Description	Inherited from CIM_ManagedElement.	For PA-RISC Servers, this string is set to "This is a PA RISC Processor, with the following details: ", followed by location-details for the processor. Location details include (where available): <ol style="list-style-type: none"> 1. Cabinet Number 2. Card Cage Number 3. Backplane Number 4. Cell Slot number 5. Slot number 6. SPU Number (as seen by the OS instance) 7. Hard Physical Address (for PA-RISC Servers)
string ElementName	Inherited from CIM_ManagedElement	For PA-RISC Servers, this string is set to "PA RISC Processor".
String Name [Key]	Inherited from CIM_Location	The location is returned as a string, of the form "<Cabinet#>:<Cell#>:<SlotNumber>" + "<Processor#>". Note that the processor# is the number assigned to the processor by that instance of the OS. For instance, on a (PA RISC) Keystone platform, could read as follows: "CabinetNumber = 0 : CellSlotNumber = 1 : SlotNumber = 0 : SPUNumber = 2".
String PhysicalPosition [Key]	Inherited from CIM_Location	A string indicating (uniquely) the position of the processor.
String CellNumber	Inherited from HP_ProcessorLocation	The number of the Cell to which the processor belongs.
String SlotNumber	Inherited from HP_ProcessorLocation	The number of the slot in which the processor rests.

table 4: HP_RealizesProcessor properties

Table 3 describes the properties of the HP_RealizesProcessor association class (associating HP_ProcessorChip and HP_Processor). It has three columns. The first is the property name (including type and units), the second is the property inheritance (indicating which class or superclass defines the property), and the third is the property's value and data source. Each row describes a property.

property name	property inheritance	property value (and data source)
HP_ProcessorChip ref Antecedent	Property of HP_RealizesProcessor	Object path of the HP_ProcessorChip Instance.
HP_Processor ref Dependent	Property of HP_RealizesProcessor	Object path of the HP_Processor Instance.

table 5: HP_ProcessorChipInLocation properties

Table 3 describes the properties of the HP_ProcessorChipInLocation association class (associating HP_ProcessorChip and HP_ProcessorLocation). It has three columns. The first is the property name (including type and units), the second is the property inheritance (indicating which class or superclass defines the property), and the third is the property's value and data source. Each row describes a property.

property name	property inheritance	property value (and data source)
HP_ProcessorChip ref Element	Property of HP_ProcessorChipInLocation	Object path of the HP_ProcessorChip Instance.
HP_ProcessorLocation ref PhysicalLocation	Property of HP_ProcessorChipInLocation	Object path of the HP_ProcessorLocation Instance.

table 6: intrinsic methods for all the CIM classes supported by CPU Instance Provider

Table 6 describes the intrinsic methods supported by this provider. It has three columns. The first is the method name, the second is a description of the provider's actions based on invoking that method, and the third is a list of any exceptions that could result from invoking the method. Each row describes a method.

Method name	description	exceptions thrown
enumerateInstances	Returns all instances of class with values of supported properties. (See tables above.)	
enumerateInstanceNames	Returns object path of all instances of class.	
getInstance	Returns an instance that matches the keys with values of supported properties. (See tables above.)	
modifyInstance	This operation is not supported by the CPU Instance Provider. This is indicated to the client, via exceptions.	CIMNotSupportedException
deleteInstance	This operation is not supported by the CPU Instance Provider. This is indicated to the client, via exceptions.	CIMNotSupportedException
createInstance	This operation is not supported by the CPU Instance Provider. This is indicated to the client, via exceptions.	CIMNotSupportedException

indications generated by this provider This Provider does not currently generate any indications.

links to more information

- WBEM information
For a CIM tutorial, go to <http://www.dmtf.org/education/cimtutorial.php>.

For additional information on HP products and services, visit us at <http://www.hp.com>.

For the location of the nearest sales office, call:

United States: +1 800 637 7740

Canada: +1 905 206 4725

Japan: +81 3 3331 6111

Latin America: +1 305 267 4220

Australia/New Zealand: +61 3 9272 2895

Asia Pacific: +8522 599 7777

Europe/Africa/Middle East: +41 22 780 81 11

For more information, contact any of our worldwide sales offices or HP Channel Partners (in the U.S., call 1 800 637 7740).



Technical information contained in this document is subject to change without notice.

© Copyright Hewlett-Packard Company 2004